

Pot Cores (5678181221)



Part Number: 5678181221

78 POT CORE SET

Pot cores have found application in all types of inductive devices. The core configuration provides a high degree of self-shielding. It also facilitates gapping to enhance utility for a variety of magnetic designs.

 \Box Pot cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicated is per pair or set.

Weight: 6.000 (g)

Dim	mm	mm tol	nominal inch	inch misc.	
A	18	±0.40	0.709		
В	5.35	±0.15	0.211		
C	13.4	±0.40	0.528	_	Chart Legend Σl/ A : Core Constant, l _e : Effective Path Length, A _e : Effective Cross- Sectional Area, Effective Core Volume
D	3.8	±0.20	0.15	_	
Е	14.9	min	0.587	min	
F	7.45	±0.15	0.293		
G	4	±0.30	0.157	_	
Н	3.2	±0.20	0.126		A _L : Inductance Factor

α 4 – 1	materiai	grade.

Electrical Properties				
$A_L(nH)$	$2600 \pm 25\%$			
Ae(cm ²)	0.43			
$\Sigma l/A(cm^{-1})$	6			
l _e (cm)	2.59			
$V_e(cm^3)$	1.12			
$A_{min}(cm^2)$	0.36			

A, value is measured at 1 kHz, B < 10 gauss.

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288

888-324-7748

845-895-2055

Fax: 845-895-2629

ferrites@fair- rite.com

www.fair- rite.com