

Pot Cores (5695140921)



Part Number: 5695140921

95 POT CORE SET

Pot cores have found application in all types of inductive devices. The core configuration provides a high degree of selfshielding. It also facilitates gapping to enhance utility for a variety of magnetic designs.

 \Box Pot cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicated is per pair or set.

Weight: 3.2.000 (g)

Dim	mm	mm tol	nominal inch	inch misc.	
A	14	±0.30	0.551		
В	4.2	±0.20	0.165		
C	9.55	±0.30	0.376		Chart Legend Σl/ A : Core Constant, l _e : Effective Path Length, A _e : Effective Cross- Sectional Area, Effective Core Volume
)	3.1	±0.20	0.122		
E	11.8	±0.40	0.465		
ſŢ.	5.9	±0.20	0.232		
G	3.3	±0.60	0.13		
Н	2.9	±0.30	0.114		A _L : Inductance Factor

Electrical Properties				
$A_L(nH)$	2100 ±25%			
Ae(cm ²)	0.251			
$\Sigma l/A(cm^{-1})$	7.9			
l _e (cm)	1.98			
$V_e(cm^3)$	0.495			
$A_{min}(cm^2)$	0.198			

 A_{r} value is measured at 1 kHz, B < 10 gauss.

Fair- Rite Products Corp. One Commercial Row, Wallkill, New York 12589-0288

888-324-7748

845-895-2055

Fax: 845-895-2629

ferrites@fair- rite.com • www.fair- rite.com